

# MA 240 Mixing amplifiers



## TECHNICAL SPECIFICATIONS



### MA 240

#### Mixing amplifier for desktop or rack mount.

Four universal line / microphone inputs with phantom power. Stereo RCA AUX input. Phoenix outputs for 100V, 70V and 4  $\Omega$  speaker lines. Priority input, tone control, REC output are integrated as well. Input for 24V DC external power supply. Useful for small and medium applications or as a component in a larger public address and voice evacuation systems

	<b>MA 240</b>
Output power	240 W
AC power consumption	600 VA
Power supply	~ 230 V / 50 Hz or 24V DC
Outputs	Low impedance output – 4 $\Omega$ (Phoenix connector) Hi impedance outputs – 100 V, 70 V, 25 V (Phoenix connector)
Inputs	<p>Microphone: Sensitivity - 50 dBu, Impedance 10 k<math>\Omega</math>, Connectors - Combi XLR</p> <p>Line: Sensitivity - 8 dBu, Impedance 10 k<math>\Omega</math>, Connectors - Combi XLR</p> <p>AUX: Sensitivity - 4 dBu, Impedance 10 k<math>\Omega</math>, Connectors - Stereo RCA</p>
Phantom power	24 V (max.)
Frequency response	80 Hz - 16 kHz
Tone control	Bass $\pm$ 10 dB, Treble $\pm$ 10 dB
THD	1 %
Signal/noise ratio	80 dB
Controls	Input level control, input gain/phantom power selector, tone control, master
Indicators	Power, output level
Dimensions	420 mm x 330 mm x 88 mm
Weight	12,8 kg